

## Demo Box Instructions

**Button 1:** Turn On/Off LED Neon Flex

**Button 2:** Turn On/Off Premier Modules & Mini Module

**Button 3:** Turn On/Off LED Ribbon

**Button 4:** Turn On/Off Hybrid LED Ribbon (Use Wizard to control dimming)

### **\*\*Entering Wizard Dimming Mode\*\***

*Step 1:* From any program selection (P01-P25 viewed on Wizard) Press and Release buttons A & B at the same time. You should now see a number from 000 to 100.

*Step 2:* Tap A to dim or brighten White (6500K).

000=off      100=brightest setting

*Step 3:* Tap B to dim or brighten Warm White (3000K)

000=off      100=brightest setting

*Step 4:* Press and Release A & B at the same time twice when finished to return to RGB Program Selection Mode.

**Button 5:** Turn On/Off Premier RGB Module and RGB Ribbon

(Use Wizard or RF Remote System to control RGB's)

### **\*\*Controlling the RGB's with the Wizard\*\***

*Step 1:* Tap A (increase) or B (decrease) to rotate through programs P01 through P25 {See Wizard Manual for P01-P25 Details}

*Step 2:* From any program selection (P01-P25 viewed on Wizard) Press and Release buttons A & B at the same time. You should now see a number from 000 to 100. You are now in Dimming Mode. Tap A to dim/brighten RGB's (000=off 100=brightest)

*Step 3:* Press and Release A & B at the same time twice when finished to return to RGB Program Selection Mode.

**Button 6:** Switch between RF Remote System and Wizard.

(This button is in center of RF Remote System, Wizard and Two Blue Ethernet Cables)

[When RF Remote System is on, the Wizard will display 0.0.1.]

{Buttons 5 must be on for RF Remote to Work}

### **\*\*Controlling the RGB's with the RF Remote System\*\***

Button 1: A) Press/Hold to turn on/off RGB LED's

B) Click once to pause on color

C) Click again to un-pause and restart program cycle

Button 2: A) Click to change program (will not work if paused on a color)

B) Press/Hold to reset to default setting

Button 3: Click to speed up color rotation

Button 5: Click to slow down color rotation

Button 4: Click to brighten RGB's

Button 6: Click to dim RGB's